



PMX-122FX

Order No.: 0202870

Price upon request

PRODUCTINFOS

Powered mixer, 2 x 475 W, 4 Ω ,

with digital amplifier and 2 DSP effect units.

- Audio mixer and digital amplifier in a metal housing
- 12 mono input channels, each with gain control, 3-way equalizer with semiparametric midrange, low cut and pan pot
- 2 stereo input channels, each with gain control, 4-way equalizer and balance control
- 2 x DSP, each with 100 different effects, e.g. reverb, hall, echo and multi-effects
- Integrated, adjustable compressor/limiter
- Adjustable stereo aux return inputs and FX send outputs
- Control room function
- Inserts for mono input channels
- Tape record/play connections
- +48 V phantom power, can be activated as required for each input channel group
- Adjustable headphone output
- 7-band graphic equalizer
- Stereo LED level display
- Connection for gooseneck light GNL-304, GNL-305 or GNL-314

tastenwelt 02/2015

“With the PMX-122FX, IMG Stage Line offers an attractive powered mixer at a favourable price. It features 12 mono channels and 2 stereo channels, thus offering sufficient options to provide a good sound for smaller bands. Various presets of internal effects are available for practical application and the master compressor provides an additional boost. The PMX-122FX is definitely worth buying due to the price-performance ratio and experience with units from this manufacturer has shown that we can expect a long service life.”

TECHNICAL SPECIFICATIONS**PMX-122FX**

No. of channels	12
No. of inputs	27
Mic input	0.5 mV, bal., 12 x 3-pole XLR
Line input	8 mV, bal. (stereo), 2 x 6.3 mm jack L/R 2 mV, bal. (mono), 12 x 6.3 mm jack
Tape (play)	60 mV, 1 x RCA L/R
Aux input	60 mV, bal., 2 x 6.3 mm jack L/R
Insert input	80 mV, 12 x 6.3 mm jack
Master output	1.5 V, bal., 1 x 3-pole XLR L/R
Aux output	10 V, 4 x 6.3 mm jack
Control room	10 V, stereo, 1 x 6.3 mm jack
Tape (rec)	680 mV, 1 x RCA L/R
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.04%
S/N ratio	89 dB
Crosstalk	-63 dB
Equalizer bass	±15 dB/80 Hz ±15 dB/100-8,000 Hz (mono channels)
Equalizer midrange	±15 dB/500 Hz (stereo channels) ±15 dB/3 kHz (stereo channels)
Equalizer treble	±15 dB/12 kHz
equalizer	±15 dB, 63/160/400 Hz 1/2.5/6.3/16 kHz
Phantom power	+48 V
Amplifier	2 x 475 W/4 Ω 2 x 260 W/8 Ω 1 x 900 W/8 Ω
Power supply	~ 230 V/50 Hz/1,250 VA

PMX-122FX

Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	1,250 VA
Admiss. ambient temp.	0-40 °C
Width	545 mm
Height	145 mm
Depth	465 mm
Weight	10.5 kg