



MMX-11USB

Order No.: 0202840

Price upon request

PRODUCTINFOS

2-channel miniature audio mixer,

with 3 inputs and USB interface.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 1 mono input channel with gain control, 2-way equalizer and pan pot, peak LED
- 1 stereo input channel with level control, 2-way equalizer and balance control
- Tape record/play connections
- 1 x 3.5 mm stereo output (master)
- Adjustable headphone output
- +20 V phantom power, permanent
- Clip LED
- Robust metal housing of compact size

TECHNICAL SPECIFICATIONS

MMX-11USB

No. of channels	2
No. of inputs	3
Mic input	0.5 mV, 1 x 3-pole XLR
Line input	150 mV (stereo), 1 x RCA L/R 2 mV (mono), 6.3 mm jack
Tape (play)	420 mV, 1 x RCA L/R
Master output	6 V max., 1 x 3.5 mm jack
Booth output	6 V max., 1 x 3.5 mm jack
Tape (rec)	1 x RCA L/R
USB	yes
Frequency range	20-20,000 Hz
THD	< 0.05%
S/N ratio	81 dB, weighted
Equalizer bass	±15 dB/80 Hz
Equalizer treble	±15 dB/12 kHz
Phantom power	+20 V
Power supply	via USB interface or via encl. power supply
Operating voltage (possible alternative)	DC 5 V
Power supply (possible alternative)	DC 500 mA
Admiss. ambient temp.	0-40 °C
Width	102 mm
Height	45 mm
Depth	140 mm
Weight	430 g